
DT471 2-Wire Monitor






DT471 Product Information




1. Parts and Functions



Key Functions

LCD screen	Display the images from outdoor station
Talk/Mon. key	 Press to talk with the visitors while receiving a call Press to monitor outdoor in standby
Unlock key	Press to release the door for visitors during talking or monitoring
Power Indicator	Light up when the monitor power-on
Microphone	Receives sound from the user
Speaker	Output sound from the outdoor
Mounting hook	Use to hang up the monitor
Connection port	Bus terminal

2. Terminal Description




L1,L2: Bus line terminal.


POW,GND:12~18V extra power connection port.
Ring,GND: Extra buzzer connection port.
SW+,SW-: Extra door bell connection port.
DIP switches: Total 6 bits can be configured.
Bit1~Bit5: User Code setting switch.

Bit6: Video impedance matching switch.

3. Mounting



<u> ②ΕΔ</u>ΣΥ



The installation height is suggested to 145~160cm.

1. Use screws to fasten the mounting bracket to the wall with mounting box.

2. Connect the 2 wire cables to the unit.

3. Mount the unit to the mounting bracket, make sure the unit is absolutely attached to the mounting bracket.

4. Specification

Power Supply:	DC 20~28V
Consumption:	Standby 1.8W;
	Working 8.16W
Screen:	7 inch digital color TFT
Resolutions:	800 X 480 pixels
Video Signal:	1Vp-p, 75Ω, CCIR standard
Wiring:	2 wires, non-polarity
Dimension:	161(H)×174(W)×22(D)mm

5. Ordering Information

Model No.	Description	Menu style
DT471/TD7	7 inch digital color TFT screen monitor with touch screen operation& white housing	Color icon

Single Package



Dimensions: 165(H)×240(W)×39(D)mm

6. Packing Information

Gross Weight: 0.55Kg

Carton Package



Carton: 258 (H)×530 (W)×340 (D)mm

Quantity: 24PCS

7. Menu Style



The copyright will be reserved to make any modifications without notice.